
IFD-NET EVO FIRMWARE UPDATE

This update is compatible with the IFD-NET EVO 80mm

You will need:

- An SD-Card
- The archive containing the backup procedure: example “IFD_EVO_FW_DDMMYYYY”

----- **UPDATE PROCEDURE** -----

Follow these steps:

- 1) Extract “IFD_EVO_FW_DDMMYYYY” archive into a formatted SD-Card (equal or more than 2Gbyte).
- 2) Switch off instrument and insert SD-Card in the dedicated slot on backside or in the SD-Card extension.
- 3) Power on instrument and wait for “<STOP>”.
- 4) Power off, remove SD-Card and reboot instrument.
- 5) To verify the firmware version enter the SETUP menu, then “UPDATE”. You will see an item like this: **SW VER 200515** “200515” is the firmware version.